



Denumire Circuit	alim. generala	Descarcatoare de supratensiuni 3P+N 50kA	C11	C12	C13	Cis1	Cis2	Cp1	Cp2	Cp3	Cp4	Cp5	Cp6	Cp8	Cr1	Cr2	Cr3	Cr4	Cr5	R1	R2	
Pi [kW]	94.4kW		1 kW	1 kW	1 kW	0.1 kW	0.1 kW	2 kW	2 kW	2 kW	2 kW	2 kW	2 kW	2 kW	2 kW	1.1 kW	1.1 kW	39 kW	9 kW	20 kW	2 kW	2 kW
Ic [A]	89A		4.6A	4.6A	4.6A	6.9A	6.9A	8.7A	8.7A	8.7A	8.7A	8.7A	8.7A	8.7A	8.7A	4.8A	4.8A	50.6A	8.5A	18.8A	9.8A	9.8A
Cablu [mmp]	CYABE 3x50+2x16		CYY-F 3x1.5	CYY-F 3x1.5	CYY-F 3x1.5	CYY-F 3x1.5	CYY-F 3x1.5	CYY-F 3x2.5	CYY-F 3x2.5	CYY-F 3x2.5	CYY-F 3x2.5	CYY-F 3x2.5	CYY-F 3x2.5	CYY-F 3x2.5	CYY-F 3x2.5	CYY-F 3x1.5	CYY-F 3x1.5	CYY-F 5X16	CYY-F 5X10	CYY-F 5X16	-	-
Protectie	4P 100A		2P 10A/30mA	2P 10A/30mA	2P 10A/30mA	1P+N 10A/30mA	1P+N 10A/30mA	2P 16A/30mA	2P 16A/30mA	2P 16A/30mA	2P 16A/30mA	2P 16A/30mA	2P 16A/30mA	2P 16A/30mA	2P 16A/30mA	2P 10A/30mA	2P 10A/30mA	4P 80A	4P 25A	4P 32A	2P 16A/30mA	2P 16A/30mA
Repartie Faza	L1,L2,L3		L1	L2	L3	L1	L2	L3	L1	L2	L3	L1	L2	L3	L1	L2	L3	L1L2L3	L1L2L3	L1L2L3	L1	L2
Destinatie	TABLORU TGD	CIRCUIT ILUMINATIA	CIRCUIT ILUMINAT	CIRCUIT ILUMINAT	CIRCUIT ILUMINAT	CIRCUIT ILUMINAT	CIRCUIT PRIZA	CIRCUIT PRIZA	CIRCUIT PRIZA	CIRCUIT PRIZA	CIRCUIT PRIZA	CIRCUIT PRIZA	CIRCUIT PRIZA	CIRCUIT PRIZA	Recuperator	Recuperator	POMPA CALDURA	TCT	TE1	REZERVA	REZERVA	



VERIFICATOR / EXPERT		NUME	SEMNATURA	CERINTA	REFERAT / EXPERTIZA NR. / DATA
Proiectant general: S.C. HAUSPLAN PROJEKT SRL Str. Stefan Greceanu, nr. 3, Ploiesti, jud Prahova		Proiectant instalatii: MJK INSTAL S.R.L. CUI:36904269 PITESTI-ARGES		Beneficiar MUNICIPIUL PLOIESTI Titlu proiect: E.T. SI D.A.L.I. - REAMENAJARE IMOBIL DIN STRADA PREDEAL NR. 28 IN UNITATE DE INVATAMANT PRESCOLAR	Pr.NR. 1017/2022 FAZA: D.A.L.I
	NUME			ADRESA: PLOIESTI, STR. PREDEAL, NR. 28	
PROIECTAT	ing. Alexandru Brebenel	S.C. HAUSPLAN PROJEKT S.R.L. PITESTI-ARGES		SCARA 1:100	TITLU PLANSA : INSTALATII ELECTRICE SCHEMA MONOFILARA TGD
DESENAT	ing. Alexandru Brebenel			10.2022	PLANSA IE-06